

KMA-8240-Z5

5-Zone Mixer Amplifier with MP3/FM Tuner/Bluetooth

The KMA-8240-Z5 is a versatile and high-performance 240W mixer amplifier designed for professional audio distribution. Combining a built-in MP3 player, FM tuner, and Bluetooth connectivity, it provides an all-in-one solution for managing multi-zone audio with ease and precision.



KEY FEATURES:

- ✓ High-performance audio with 5-zone distribution control.
- ✓ Built-in Bluetooth, FM tuner, USB, and SD playback.
- ✓ 3 MIC inputs with priority muting and dual AUX ports.
- ✓ Precision bass, treble, and individual zone management.
- ✓ Integrated safety against overload and overheating.

IDEAL FOR:

-  Retail
-  School
-  Restuarants
-  Offices
-  Public Adress System



LED INDICATORS



BLUETOOTH & USB



MIC INPUTS



5-ZONE



COOLING FAN



FM TUNER

Rated output power	240W
Output	Low impedance : 4-16Ω 70V : 19Ω 100V : 39Ω
AUX output level	0.775V (0dBV)
5 Zone Output	100V
Input level	MIC 1,2,3 : 600Ω, 10-15mV (unbalanced) AUX 1,2 : 10KΩ, 200-470mV (unbalanced)
Extra Input	SD slot, USB slot, RCA connector
Frequency response	60Hz-15KHz (±3dB)
T.H.D.	<0.5% at 1KHz, 1/3 rated output power
S/N ratio	MIC 1,2,3 : ≥72dB AUX 1,2 : ≥85dB
Tone	Bass : ±10dB at 100Hz Treble : ±10dB at 12KHz
Muting Function	MIC1 overrides other input signals at 0~30dB
Controls	Volume, tone/treble, mute, power
Protection	AC fuse, Overload, Short circuit, high temperature FUSE×6A
Cooling Fan	DC 12V FAN
LED indicator	AC: POWER, level: 2、4、6、8、10
Power supply	AC220~240V, 50-60Hz
Power consumption	350W
Power cord	(3×0.75 mm2)×1.5M (standard)
Product dimension (mm)	89(H)×483(W)×366(D)
Packaging dimension (mm)	185(H)×520(W)×435(D)
Net weight (kg)	13.8
Packaging weight (kg)	15.40